

SDL

Lighting

PowerDriverPlus 36

High Power 36 LED Driver with DMX 512



PowerDriver 36 is a purpose designed LED driver capable of driving up to 36 Luxeon 1 Watt LED's. The unit has a built in DMX 512 interface. The powerdriver 36 can drive wall washing, spot lighting or MR16 RGB Downlighter modules. It has built in pre set colours, cycle, and cross fade settings with variable speed.

Specifications

Input

Voltage	85 – 265 V ac
Frequency	50 – 60 Hz
Power Consumption range	6 – 55 Watts
Power Factor	0.95
Efficiency	88%
Ambient Temperature	-20 to +50 Degrees Centigrade

Output

Power output range	4.8 – 14.6 W Per Channel
Output Current	350mA @ 100%
Output Voltage	14 – 52 Vdc