

SDL

Lighting

PowerDriver 36

High Power 36 LED Driver with DMX 512



PowerDriver 36



PowerDriver 36

PowerDriver 36 is a purpose designed LED driver capable of driving up to 36 Luxeon 1 Watt LED's. The unit has a built in DMX 512 interface. The powerdriver 36 can drive wall washing, spot lighting or MR16 RGB Downlighter modules.

Specifications

Input

Voltage	195 – 265 V ac
Frequency	50 – 60 Hz
Power Consumption range	6 – 54 Watts
Power Factor	0.95
Efficiency	80%
Ambient Temperature	-20 to +85 Degrees Centigrade

Output

Power output range	4.8 – 14.4 W Per Channel
Output Current	350mA @ 100%
Output Voltage	48Vdc